Technical Specification

Product Code: VPBN100BK

Description: 115V/230V Dual Voltage Shaver Socket Outlet

Luckinslive 389109185





General Information

Dimensions (mm)	91 (W) x 149 (H) x 45 (D)
Plate Dimensions (mm)	88 (W) x 146 (H) x 8 (D)
Dimensions With Gasket (mm)	91 (W) x 149 (H) x 9 (D)
Plate Fixing Centres - Vertical (mm)	120.6
Style	Victorian
Finish	Black Nickel
Insert Colour	Black
Gasket Colour	Black
Supplied Fixing Screw Finish	Black Nickel
Materials	Front Plate: Stainless Steel Terminals: Brass Contacts: Silver "on-lay" Copper / Brass Earth Strap: Mild Steel
	Insert & Rear Housing: Urea Terminal Screws: Steel & Yellow Passivated Internal Busbars: Formed Pressed Brass Gasket: Nylon
Anti Microbial Certified	No
Operating Voltage (AC)	220-240
Frequency (Hz)	50/60
Load Rating @115V (Va)	20
Load Rating @230V (Va)	20
Thermal Protection Device	PTC Resettable Fuse
Termination Type	Screw
Terminal Size (mm)	Ø3.5
Terminal Torque Value (Nm)	0.5
Terminal Capacity - Solid (mm^2)	2 x 1.5 or 1 x 2.5
Socket Features	Safety Interlock Shutter
Twin Earth Terminals	Yes
Product Marking	Shavers Only, 230V~, 115V~
Minimum Back Box Depth (mm)	47
Ingress Protection	IP20
Operational Temperature (°C)	-5 to +40
Warranty (Years)	20
Warranty - Electronics (Years)	2

Standards BS EN IEC 61558-1, BS EN 61558-2-5

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
This outlet is not continuously rated and therefore not suitable for use as a permanent charging outlet.
CLICK dual voltage shaver outlets incorporate a double wound isolating transformer rated 20Va at 230V or 115V and meets BS EN 61558-2-5:2010 making it safe for use in bathrooms.
PTC resettable fuses increase resistance as temperature increases due to increased flow. PTC resettable fuses are designed to limit unsafe currents while allowing constant safe current levels, resistance will "reset" automatically when the fault is removed and temperature returns to a safe level.
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

Scolmore House, Mariner, Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7UL United Kingdom
T: +44 (0)1827 63454 | **F:** +44 (0)1827 63362
E: sales@scolmore.com | **W:** scolmore.com

CLICK OR SCAN Catalogue Range DoC Installation CLICK OR SCAN