essentials™

Technical Specification

Product Code: CL1835 Luckinslive 406093077

Description: 13A 1 Gang Double Pole Safety Shutter Switched Socket Outlet With Neon



General Information

Dimensions (mm)	80 (W) x 80 (H) x 42 (D)		
Plate Fixing Centres - Horizontal (mm)	60.3		
Style	Metal Clad		
Colour	Grey		
Insert Colour	White		
Supplied Fixing Screw Finish	Polished Chrome		
Materials	Front Plate & Back Box: Electrophoretically Coated Steel		Insert & Rocker Switch: Urea
	Rear Housing: Urea		Terminals: Brass
	Terminal Screws: Steel & Yellow Passivated		Contacts: Silver "on-lay" Copper / Brass
	Internal Busbars: Formed Pressed Brass		Earth Strap: Mild Steel
Operating Voltage (AC)	250	Frequency (Hz)	50
Resistive Load Rating (A)	13		
Termination Type	Screw		
Terminal Size (mm)	Ø5	Terminal Torque Value (Nm)	2
Terminal Capacity - Solid (mm^2)	3 x 2.5 or 2 x 4		
Double Pole Switch	Yes		
3 Pin Safety Shuttered	Yes		
Supplied Back Box Depth (mm)	40		
Back Box Knockouts - Total (mm)	5 x Ø20		
Back Box Knockouts - Top (mm)	2 x Ø20	Back Box Knockouts - Bottom (mm)	1 x Ø20
Back Box Knockouts - Rear (mm)	None	Back Box Knockouts - Sides (mm)	1 x Ø20
Back Box Earth Terminal Supplied	Yes		
Ingress Protection	IP20		
Operational Temperature (°C)	-5 to +40		
Warranty (Years)	20		

Standards BS 1363-2

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

The safety shutter will only fully open when all three BS 1363 plug-top pins engage correctly with the shutter. Inserting the earth pin alone will not open the live and neutral shutter like conventional socket shutters.

Scolmore House, Mariner, Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7UL United Kingdom
T: +44 (0)1827 63454 | **F:** +44 (0)1827 63362
E: sales@scolmore.com | **W:** scolmore.com

CLICK OR SCAN Catalogue Range DoC Installation CLICK OR SCAN