essentials™

Technical Specification

Product Code: CL785 Luckinslive 435925682

Description: 13A 1 Gang Switched Socket Outlet With Type A & C USB (4A) Outlets





General Information

Dimensions (mm)	80 (W) x 80 (H) x 42 (D)		
Plate Fixing Centres - Horizontal (mm)	60.3		
Style	Metal Clad		
Colour	Grey		
Insert Colour	White		
Supplied Fixing Screw Finish	Polished Chrome		
Materials	Front Plate & Back Box: Electrophoretically Coated Steel	Insert & Rocker Switch: Urea	
	Housing: Nylon	Terminals: Brass	
	Terminal Screws: Steel & Yellow Passivated	Contacts: Silver "on-lay" Copper / Brass	
	Internal Busbars: Formed Pressed Brass	PCB: Mixed Components	
	Earth Strap: Mild Steel		
Operating Voltage (AC)	250	Frequency (Hz)	50
Resistive Load Rating (A)	13		
USB Output Type	USB Type 'A' & Type 'C'		
USB Number Of Outputs	2	USB Charging Total Load (A)	4
USB Charging Voltage (V DC)	5	USB Standby Current (W)	0.1
Termination Type	Screw		
Terminal Size (mm)	Ø5	Terminal Torque Value (Nm)	1.2
Terminal Capacity - Solid (mm^2)	3 x 2.5 or 2 x 4		
Single Pole Switched	Yes		
3 Pin Safety Shuttered	Yes		
Twin Earth Terminals	Yes		
Product Marking	5V DC 4A (SHARED)		
Supplied Back Box Depth (mm)	40		
Back Box Knockouts - Total (mm)	5 x Ø20		
Back Box Knockouts - Top (mm)	2 x Ø20	Back Box Knockouts - Bottom (mm)	1 x Ø20
Back Box Knockouts - Rear (mm)	None	Back Box Knockouts - Sides (mm)	1 x Ø20
Back Box Earth Terminal Supplied	Yes		
Ingress Protection	IP20		
Operational Temperature (°C)	-5 to +40		
Warranty (Years)	20	Warranty - Electronics (Years)	2

Standards BS 1363-2, BS EN IEC 62368-1, BS EN 62680-1-1

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
The USB circuits within this socket outlet are designed to withstand insulation resistance tests at 500V.
Intelligent chip incorporated within the USB PCB adjusts the output according to the load connected.
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.
Independent Charging: 5V DC, 4A – USB Type A (2.4A), USB Type C (3A)
Dual Charging: 5V DC, 4A - USB Type A (1.2A), USB Type C (3A)

Scolmore House, Mariner, Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7UL United Kingdom
T: +44 (0)1827 63454 | **F:** +44 (0)1827 63362
E: sales@scolmore.com | **W:** scolmore.com

CLICK OR SCAN Catalogue Range DoC Installation CLICK OR SCAN