# Technical Specification

Product Code: VPSC100BK

Luckinslive 389115483

Description: 115V/230V Dual Voltage Shaver Socket Outlet






## General Information

| | | | |
|---|---|---|---|
| Dimensions (mm) | 91 (W) x 149 (H) x 45 (D) | | |
| Plate Dimensions (mm) | 88 (W) x 146 (H) x 8 (D) | | |
| Dimensions With Gasket (mm) | 91 (W) x 149 (H) x 9 (D) | | |
| Plate Fixing Centres - Vertical (mm) | 120.6 | | |
| Style | Victorian | | |
| Finish | Satin Chrome | | |
| Insert Colour | Black | | |
| Gasket Colour | Black | | |
| Supplied Fixing Screw Finish | Polished Chrome | | |
| Materials | Front Plate: Stainless Steel | Insert & Rear Housing: Urea | |
| | Terminals: Brass | Terminal Screws: Steel & Yellow Passivated | |
| | Contacts: Silver "on-lay" Copper / Brass | Internal Busbars: Formed Pressed Brass | |
| | Earth Strap: Mild Steel | Gasket: Nylon | |
| Anti Microbial Certified | No | | |
| Operating Voltage (AC) | 220-240 | Frequency (Hz) | 50/60 |
| Load Rating @115V (Va) | 20 | | |
| Load Rating @230V (Va) | 20 | | |
| Thermal Protection Device | PTC Resettable Fuse | | |
| Termination Type | Screw | | |
| Terminal Size (mm) | Ø3.5 | Terminal Torque Value (Nm) | 0.5 |
| Terminal Capacity - Solid ($mm^2$) | 2 x 1.5 or 1 x 2.5 | | |
| Socket Features | Safety Interlock Shutter | | |
| Twin Earth Terminals | Yes | | |
| Product Marking | Shavers Only, 230V~, 115V~ | | |
| Minimum Back Box Depth (mm) | 47 | | |
| Ingress Protection | IP20 | | |
| Operational Temperature (°C) | -5 to +40 | | |
| Warranty (Years) | 20 | Warranty - Electronics (Years) | 2 |

**Standards** BS EN IEC 61558-1, BS EN 61558-2-5

## Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
This outlet is not continuously rated and therefore not suitable for use as a permanent charging outlet.
CLICK dual voltage shaver outlets incorporate a double wound isolating transformer rated 20Va at 230V or 115V and meets BS EN 61558-2-5:2010 making it safe for use in bathrooms.
PTC resettable fuses increase resistance as temperature increases due to increased flow. PTC resettable fuses are designed to limit unsafe currents while allowing constant safe current levels, resistance will "reset" automatically when the fault is removed and temperature returns to a safe level.
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

UK Design Registration: 3015621

Scolmore House, Mariner, Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7UL United Kingdom
**T:** +44 (0)1827 63454 | **F:** +44 (0)1827 63362
**E:** sales@scolmore.com | **W:** scolmore.com

CLICK OR SCAN Catalogue Range DoC Installation CLICK OR SCAN