

# Product datasheet

Specifications



Head for emergency switching off push button, Harmony XAC, red mushroom 40mm, latching turn to release, unmarked

ZA2BS844

## Main

Range of product	Harmony XAC
Product or component type	Head for emergency switching off push-button
Sale per indivisible quantity	1

## Complementary

Product compatibility	XACA..
Mounting location	Front of enclosure
Overvoltage category	Class II conforming to IEC 61140
Operator profile	Red mushroom Ø 40 mm
Net weight	0.05 kg
Marking	Unmarked

## Environment

Ambient air temperature for storage	-40...70 °C
Ambient air temperature for operation	-25...70 °C
IK degree of protection	IK08
Standards	IEC 60204-32 IEC 60947-5-1 CSA C22.2 No 14 UL 508 IEC 60947-5-5 IEC 62262
Vibration resistance	15 gn (f= 10...500 Hz) conforming to IEC 60068-2-6

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.100 cm
Package 1 Width	11.000 cm
Package 1 Length	10.000 cm
Package 1 Weight	45.000 g
Unit Type of Package 2	S01
Number of Units in Package 2	40
Package 2 Height	15.000 cm

---

Package 2 Width	15.000 cm
-----------------	-----------

---

Package 2 Length	40.000 cm
------------------	-----------

---

Package 2 Weight	1.940 kg
------------------	----------

---

## Logistical informations

---

Country of origin	FR
-------------------	----

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Carbon footprint (kg.eq.CO2 per CR, Total Life cycle) 1

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging without single use plastic No

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

REACH Regulation [REACH Declaration](#)

## Use Again

### Repack and remanufacture

Circularity Profile [End of Life Information](#)

Take-back No